

70mm

gorsun®

HIGH PERFORMANCE FOLDABLE
MINI BLUETOOTH HEADSET

产品名称: E86蓝牙耳机
主要功能: 蓝牙 (通话)+AUX
AUX功能: 不开机插上即可使用; 开机后插入AUX线自动关闭蓝牙功能
开机状态: 5分钟无设备连接自动关机

产品参数:





支持协议: ACRCP1.3/A2DP1.0/HFP1.5/HSP1.0
有效范围: 8-10m
工作频率: 2.402-2.180GHz
电池规格: 3.7V/400mAh (内置可充电锂电池)
充电时间: ≈2h
续航时间: 12h

灵敏度: 102±3dB/mW
电阻: 32ohm
喇叭直径: 40mm





包装清单

1. 一个蓝牙耳机主机
2. 一根USB充电线
3. 一本使用说明书



按键说明

1. “” 开启/关闭
2. “” 长按上一曲/短按减音量
3. “” 长按下一曲/短按加音量
4. “” 暂停/播放

按键指引

1. 接通电话: 来电时短按 “”;
2. 挂断电话: 通话中短按 “”;
3. 回拨最后一次通话号码: 双击 “”;
4. 播放音乐: 正常状态下短按 “”, 自动打开智能设备播放音乐;
5. 通话后继续播放: 来电时, 自动暂停播放中的音乐, 通话结束后, 自动继续播放。

功能说明

开机: 长按 “” 三秒以上, 设备启动并自动进入蓝牙模式, LED指示灯蓝灯长亮。
关机: 长按 “” 三秒以上, LED指示灯熄灭, 设备关闭。

蓝牙模式

1. 首次配对: 开机后, 语音提示: “Power on, Pairing”, 打开智能设备的蓝牙功能, 开启搜索并选择设备 “GS”, LED指示灯红蓝交替闪烁, 耳机自动进入蓝牙配对模式, 无需密码, 配对成功后语音提示 “Connected” LED指示灯蓝色闪烁。
2. 重新配对: 关闭已连接智能设备的蓝牙功能, 此时, 蓝牙耳机与上次配对设备断开连接, LED指示灯蓝红闪烁进入配对模式, 打开新的智能设备的蓝牙功能, 开启搜索并选择设备 “GS”, 重复首次配对操作即可。
3. 后续配对: 开机后1秒内, 会自动搜索并连接最后一次与之配对的设备;
4. 最大音量警示音: “didi”;

5. 省电模式: 匹配状态持续5分钟无任何操作, 耳机自动关机; 插入AUX-in线自动切断供电;
6. 全解码支持MP3、WAV、WMA、FLAC格式;
7. IOS系统电量显示;
8. 国际通用Micro USB充电口。

TF卡播放模式

关机情况下, 插入TF卡, 短按开机按钮三秒左右, 蓝牙耳机自动进入TF卡播放模式;
开机情况下, 插入TF卡, 蓝牙耳机自动进入TF卡播放模式。

注意: TF卡最大支持容量为16GB, 如使用超过16GB的TF卡, 有可能导致系统无法播放音乐

AUX-in播放模式

在任意模式下, 插入AUX-in线, 耳机自动关机, 切换到AUX-in功能, 此时无需耗电。

LED灯状态

充电状态	红色LED指示灯长亮, 满电时, 指示灯熄灭
开机状态	蓝色LED指示灯长亮
关机提示	LED指示灯熄灭
配对状态	红蓝LED指示灯交替闪烁
连接成功	蓝色LED指示灯长亮
使用状态	Bluetooth Mode, 蓝色LED指示灯闪烁 AUX-in Mode, 耳机自动关机, LED指示灯熄灭

注意事项

1. 蓝牙耳机进入配对模式后若无配对连接操作, 请关闭设备避免电量损耗;
2. 搜索蓝牙耳机时, 不要进行其他操作, 以免程序出错;
3. 在使用中请选择适当音量, 以防对耳朵造成伤害;
4. 请注意蓝牙耳机的良好使用环境, 以防对耳机造成伤害;
5. 长时间未使用耳机, 请先将耳机充满电后再使用。

70mm

gorsun®

HIGH PERFORMANCE FOLDABLE
MINI BLUETOOTH HEADSET

Product Name: E86 Bluetooth headphone
Function: Bluetooth (call) and AUX
AUX function: It can be used without powering on, and will automatically power-off after using AUX cable.
Power on status: auto power-off after disconnected for 5 minutes.

Specifications





Supporting :ACRCP1.3/A2DP1.0/HFP1.5/HSP1.0
Working Range: up to 8-10m
Frequency Response: 2.402-2.180GHz
Battery Voltage: 3.7v / 400mAh (Built in rechargeable lithium battery)
Charging Time: about 2 hours
Working Time: about 12 hours

Sensitivity: 102±3 dB/mW
Impedance: 32ohm
Speaker diameter: 40mm





Packing list

1. A Bluetooth Headphone
2. An USB charging data cable
3. An User manual


Button Function:


1. “” Power on/Power off
2. “” Move previous: long press
Volume down: short press
3. “” Move next: long press
Volume up: short press
4. “” Pause / play

Button Guide

1. Hang on: Short press “” button when being called
2. Hang up: Short press “” button when calling
3. Dial back: Double click “” button
4. Play music: Normally short press “” button to turn on the smart devices automatically to play music
5. Continue to play music after the call: When there is an incoming call, the music will be automatically suspended. After the call, it will continue playing.

Function Description

Power on: Long press “” for more than 3 seconds, the headphone turn on and enter Bluetooth

Mode, Blue LED is on
Power off: Long press “” for more than 3 seconds, the LED indicator light is off and the headphone turn off.

Bluetooth mode

1. First pairing: after power on, the voice will prompt “**Power on, Pairing**” to get into bluetooth pairing mode with blue and red light flashing alternately. Then turn on the bluetooth function of the smart devices to search the pairing name “**GS**” for connecting, after pairing successfully, the voice will prompt “Connected” with blue light flashing.
2. Repairing: turn off the Bluetooth function of the connected smart devices, at this time, the Bluetooth headset and the last connecting device got disconnected, the light flashes between red and blue, and enter the Bluetooth pairing mode, then redo the operation of First Pairing to search the pairing name “**GS**” for connecting.

3. Subsequent pairing: 1 seconds after powering on, it will automatically search and connect the smart device which paired last time.

4. Warning voice of maximum volume: “Didi”

5. Power saving mode: headset will automatically power off after pairing continuously for 5 minutes; it will cut off power supply automatically after using Aux-in cable for power saving.

6. WMP support MP3, WAV, WMA and FLAC.

7. Power display on IOS system.

8. International general Micro USB charging port.

TF card play mode

When powering off, insert TF card, short press the power button about three seconds, the Bluetooth headset automatically enter the TF card play mode;
When powering on, insert TF card, Bluetooth headset automatically enter the TF play mode.

Note: the maximum capacity of TF card is 16GB, which beyond 16GB, may fail to play music

AUX - in Mode

In any modes, insert the AUX-in line, the headset automatically shut down, and switch to AUX-in function without power consumption.

LED light status

Charging	The red LED is on, when full charged, the indicator light is off
Powering on	Blue LED flashes
Powering off	Red LED flashes and finally turn to off

Pairing	Blue and red LED flashes alternately
Connected	Blue LED is on
Working	Bluetooth Mode, blue LED flashes AUX-in Mode, headphone turn off automatically, LED indicator light is off

Note

1. Please turn off the device to avoid power consumption if no pairing operation taken after bluetooth headset entering into the pairing mode.
2. Please do not make other operations when searching bluetooth in case of procedure error.
3. Please adjust volume appropriately to avoid doing harm to the ears.
4. Please pay attention to choose a good surroundings for bluetooth headset use to avoid causing damage to the headset.
5. Please get bluetooth headset full charged firstly when it has not being used for a long time before.

说明书规格: 单色双面印刷, 70*70mm 风琴折。